

# HDM3065-3000V-50A 六位半高精度大电压大电流数字万用表



DCA 最大量程 50A，DCV 最大量程 3000V；六位半读数万用表，0.1  $\mu$ V 分辨率；30 k/s 高速采集，利于捕捉瞬态信号；输入端口前后两套，便于测试系统布线；标配条形图、直方图、趋势图和数据统计功能；双显示测量功能，同时显示电压和频率；多种测量功能：直流电压、交流电压、直流电流、交流电流、2 线电阻、4 线电阻、电容、二极管、连通性、频率、周期、温度；4.3 寸 64K 色液晶屏；操作简单，测量接口丰富。

- 测量直流电流最大 50A;
- 测量直流电压最大量程 3000V;
- 万用表输入端口前后两套, 便于测试系统布线;
- 30 k/s 高速采集, 利于捕捉瞬态信号;
- 标配条形图、直方图、趋势图和数据统计功能;
- 双显示测量功能, 可同时显示电压和频率测量值;
- 交流电压真有效值和交流电流真有效值测量;
- 0.1  $\mu$ V 分辨率, 操作简单, 参数可灵活设置;
- 多种测量功能: 直流电压、交流电压、直流电流、交流电流、2 线电阻、4 线电阻、电容、二极管、连通性、频率、周期、温度;
- 4.3 寸 64 K 色 TFT 液晶屏;
- 支持 SCPI 远程控制命令、兼容市场上的主流万用表命令集, 标配电脑端上位机控制软件;
- 配置接口: USB Device, USB Host, RS232/485, LAN, GPIB (选配)。

#### 技术参数

型号:	HDM3065-3000V-50A
最大直流电流	50A
直流电压测量范围、精度	100mV-3000V,0.004%
直流电流测量范围、精度	100 $\mu$ A-50A, 0.5%
交流电压测量值	True-RMS, 100mV, 1V, 10V, 100V, 750V
交流电流测量值	True-RMS, 100 $\mu$ A, 1mA, 10mA, 100mA, 1A, 3A, 10A
电阻测量范围、精度	100 $\Omega$ -100 M $\Omega$ , 0.01%
电容测量	1nF, 10nF, 100nF, 1 $\mu$ F, 10 $\mu$ F, 100 $\mu$ F
连通性测试	量程固定在 1 K $\Omega$
二极管测试	0-5V 阈值可设置
频率测试	3Hz-300 KHz
周期测试	1 $\mu$ s-0.33s

温度测量	支持热电偶和热电阻测量
多种测量功能	直流电压、交流电压、直流电流、交流电流、2 线电阻、4 线电阻、电容、二极管、连通性、频率、周期、温度
显示	4.3 寸 64 K 色 TFT 液晶屏
读数分辨率	六位半 (0.1 $\mu$ V)
存储器	10, 000 个读数/秒
标配接口	USB、RS232/485、LAN
选配接口	GPIB

# Specifications HDM3065-3000V-50A

DM3065 accuracy specifications:  $\pm$  (% of reading + % of range)<sup>1</sup>.

Range <sup>2</sup> /frequency		24 hours <sup>3</sup> T <sub>CAL</sub> $\pm$ 1 °C	90 days T <sub>CAL</sub> $\pm$ 5 °C	1 year T <sub>CAL</sub> $\pm$ 5 °C	2 years T <sub>CAL</sub> $\pm$ 5 °C	Temperature coefficient/°C <sup>4</sup>
DC voltage Front Panel	DC voltage Rear Panel					
100 mV		0.0030 + 0.0030	0.0040 + 0.0035	0.0050 + 0.0035	0.0065 + 0.0035	0.0005 + 0.0005
1 V	400mV	0.0020 + 0.0006	0.0030 + 0.0007	0.0040 + 0.0007	0.0055 + 0.0007	0.0005 + 0.0001
10 V	4 V	0.0015 + 0.0004	0.0020 + 0.0005	0.0035 + 0.0005	0.0050 + 0.0005	0.0005 + 0.0001
100 V	40 V	0.0020 + 0.0006	0.0035 + 0.0006	0.0045 + 0.0006	0.0060 + 0.0006	0.0005 + 0.0001
1000 V	400 V	0.0020 + 0.0006	0.0035 + 0.0010	0.0045 + 0.0010	0.0060 + 0.0010	0.0005 + 0.0001
	3000 V <sup>16</sup>	0.020+0.006	0.035+0.010	0.045+0.010	0.060+0.010	0.005+0.001

## True RMS AC voltage <sup>2,5,6</sup>

100 mV, 1 V, 10 V, 100 V, and 750 V ranges

5 Hz to 10 Hz	0.35 + 0.02	0.35 + 0.03	0.35 + 0.03	0.35 + 0.03	0.035 + 0.003
10 Hz to 20 kHz	0.04 + 0.02	0.05 + 0.03	0.06 + 0.03	0.07 + 0.03	0.005 + 0.003
20 kHz to 50 kHz	0.10 + 0.04	0.11 + 0.05	0.12 + 0.05	0.13 + 0.05	0.011 + 0.005
50 kHz to 100 kHz	0.55 + 0.08	0.60 + 0.08	0.60 + 0.08	0.60 + 0.08	0.060 + 0.008
100 kHz to 300 kHz	4.00 + 0.50	4.00 + 0.50	4.00 + 0.50	4.00 + 0.50	0.200 + 0.020

## Resistance <sup>7</sup>

### Test current

100 $\Omega$	1 mA	0.0030 + 0.0030	0.008 + 0.004	0.010 + 0.004	0.012 + 0.004	0.0006 + 0.0005
1 k $\Omega$	1 mA	0.0020 + 0.0005	0.008 + 0.001	0.010 + 0.001	0.012 + 0.001	0.0006 + 0.0001
10 k $\Omega$	100 $\mu$ A	0.0020 + 0.0005	0.008 + 0.001	0.010 + 0.001	0.012 + 0.001	0.0006 + 0.0001
100 k $\Omega$	10 $\mu$ A	0.0020 + 0.0005	0.008 + 0.001	0.010 + 0.001	0.012 + 0.001	0.0006 + 0.0001
1 M $\Omega$	5 $\mu$ A	0.002 + 0.001	0.008 + 0.001	0.010 + 0.001	0.012 + 0.001	0.0010 + 0.0002
10 M $\Omega$	500 nA	0.015 + 0.001	0.020 + 0.001	0.040 + 0.001	0.060 + 0.001	0.0030 + 0.0004
100 M $\Omega$	500 nA    10 M $\Omega$	0.300 + 0.010	0.800 + 0.010	0.800 + 0.010	0.800 + 0.010	0.1500 + 0.0002

## DC current

### Burden voltage

100 $\mu$ A	< 0.03 V	0.010 + 0.020	0.040 + 0.025	0.050 + 0.025	0.060 + 0.025	0.0020 + 0.0030
1 mA	< 0.3 V	0.007 + 0.006	0.030 + 0.006	0.050 + 0.006	0.060 + 0.006	0.0020 + 0.0005
10 mA	< 0.05 V	0.007 + 0.020	0.030 + 0.020	0.050 + 0.020	0.060 + 0.020	0.0020 + 0.0020
100 mA	< 0.5 V	0.010 + 0.004	0.030 + 0.005	0.050 + 0.005	0.060 + 0.005	0.0020 + 0.0005
1 A	< 0.7 V	0.050 + 0.006	0.080 + 0.010	0.100 + 0.010	0.120 + 0.010	0.0050 + 0.0010
3 A	< 2.0 V	0.180 + 0.020	0.200 + 0.020	0.200 + 0.020	0.230 + 0.020	0.0050 + 0.0020
10 A <sup>8</sup>	< 0.5 V	0.050 + 0.010	0.120 + 0.010	0.120 + 0.010	0.150 + 0.010	0.0050 + 0.0010
50 A <sup>17</sup>	< 5 V	0.50+0.10	1.2+0.1	1.2+0.1	1.5+0.1	0.05+0.01

## Capacitance <sup>15</sup>

1.0000 nF	0.50 + 0.50	0.50 + 0.50	0.50 + 0.50	0.50 + 0.50	0.05 + 0.05
10.000 nF	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.05 + 0.01
100.00 nF	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.05 + 0.01
1.0000 $\mu$ F	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.05 + 0.01
10.000 $\mu$ F	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.05 + 0.01
100.00 $\mu$ F	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.40 + 0.10	0.05 + 0.01

## Specifications HDM3065-3000V-50A (Continued)

Range <sup>2</sup> /frequency	24 hours <sup>3</sup> T <sub>CAL</sub> ± 1 °C	90 days T <sub>CAL</sub> ± 5 °C	1 year T <sub>CAL</sub> ± 5 °C	Temperature coefficient/°C <sup>4</sup>	
<b>True RMS AC current <sup>2, 6, 9</sup></b>					
Range	Freq				
100.0000uA	3Hz-5Hz	1.10 + 0.06	1.10 + 0.06	1.10 + 0.06	0.200 + 0.006
	5Hz-10Hz	0.35 + 0.06	0.35 + 0.06	0.35 + 0.06	0.100 + 0.006
	10Hz-5kHz	0.15 + 0.06	0.15 + 0.06	0.15 + 0.06	0.015 + 0.006
	5kHz-10kHz	0.35 + 0.70	0.35 + 0.70	0.35 + 0.70	0.030 + 0.006
1.000000mA	3Hz-5Hz	1.00 + 0.04	1.00 + 0.04	1.00 + 0.04	0.100 + 0.006
	5Hz-10Hz	0.30 + 0.04	0.30 + 0.04	0.30 + 0.04	0.035 + 0.006
	10Hz-5kHz	0.12 + 0.04	0.12 + 0.04	0.12 + 0.04	0.015 + 0.006
	5kHz-10kHz	0.20 + 0.25	0.20 + 0.25	0.20 + 0.25	0.030 + 0.006
10.00000mA	3Hz-5Hz	1.10 + 0.06	1.10 + 0.06	1.10 + 0.06	0.200 + 0.006
	5Hz-10Hz	0.35 + 0.06	0.35 + 0.06	0.35 + 0.06	0.100 + 0.006
	10Hz-5kHz	0.15 + 0.06	0.15 + 0.06	0.15 + 0.06	0.015 + 0.006
	5kHz-10kHz	0.35 + 0.70	0.35 + 0.70	0.35 + 0.70	0.030 + 0.006
100.0000mA	3Hz-5Hz	1.00 + 0.04	1.00 + 0.04	1.00 + 0.04	0.100 + 0.006
	5Hz-10Hz	0.30 + 0.04	0.30 + 0.04	0.30 + 0.04	0.035 + 0.006
	10Hz-5kHz	0.10 + 0.04	0.10 + 0.04	0.10 + 0.04	0.015 + 0.006
	5kHz-10kHz	0.20 + 0.25	0.20 + 0.25	0.20 + 0.25	0.030 + 0.006
1-3.000000A	3Hz-5Hz	1.10 + 0.06	1.10 + 0.06	1.10 + 0.06	0.100 + 0.006
	5Hz-10Hz	0.35 + 0.06	0.35 + 0.06	0.35 + 0.06	0.035 + 0.006
	10Hz-5kHz	0.15 + 0.06	0.15 + 0.06	0.15 + 0.06	0.015 + 0.006
	5kHz-10kHz	0.35 + 0.70	0.35 + 0.70	0.35 + 0.70	0.030 + 0.006
10.00000A	3Hz-5Hz	1.10 + 0.08	1.10 + 0.10	1.10 + 0.10	0.100 + 0.008
	5Hz-10Hz	0.35 + 0.08	0.35 + 0.10	0.35 + 0.10	0.035 + 0.008
	10Hz-10kHz	0.15 + 0.08	0.15 + 0.10	0.15 + 0.10	0.015 + 0.008
<b>Continuity</b>					
1 kΩ	0.002 + 0.030	0.008 + 0.030	0.010 + 0.030	0.012 + 0.030	0.0010 + 0.0020
<b>Diode test <sup>10</sup></b>					
5 V	0.002 + 0.030	0.008 + 0.030	0.010 + 0.030	0.012 + 0.030	0.0010 + 0.0020
<b>DC ratio (typ)</b>					
(normalized input accuracy) + (normalized reference accuracy)					
<b>Temperature <sup>11</sup></b>					
PT100 (DIN/ IEC 751)	Probe accuracy + 0.05 °C				
5 kΩ thermistor	Probe accuracy + 0.1 °C				
<b>Frequency: specification ± (% of reading) <sup>12, 13</sup></b>					
<b>100 mV, 1 V, 10 V, 100 V, and 750 V ranges <sup>14</sup></b>					
10 to 100 Hz	0.030	0.030	0.030	0.030	0.035
100 Hz to 1 kHz	0.003	0.008	0.010	0.010	0.015
1 to 300 kHz	0.002	0.006	0.010	0.010	0.015
Square wave <sup>15</sup>	0.001	0.006	0.010	0.010	0.015
<b>Additional gate time errors ±(% of reading) <sup>13</sup></b>					
<b>Frequency</b>	<b>1 second</b>	<b>0.1 second</b>	<b>0.01 second</b>		
3 Hz to 40 Hz	0	0.200	0.200		
40 Hz to 100 Hz	0	0.060	0.200		
100 Hz to 1 kHz	0	0.020	0.200		
1 kHz to 300 kHz	0	0.004	0.030		
Square wave <sup>15</sup>	0	0	0		

## Specifications HDM3065-3000V-50A (Continued)

1. For DC: Specifications are for 60-minute warm-up, aperture of 10 or 100 NPLC, and auto zero on. For AC: Specifications are for 60-minute warm-up, slow AC filter, sine wave.
2. 20% over range on all ranges, except 1,000 V DCV, 750 ACV, 10 A DC, 3 A AC, 10 A AC, and diode test.
3. Relative to calibration standards.
4. Add this for each °C outside TCAL  $\pm 5$  °C.
5. Specifications are for sinewave input  $> 5\%$  of range . 750 ACV range limited to  $8 \times 10^7$  Volt-Hz.  
For inputs within 1% and 5% of range and 50 kHz, add 0.1% of range additional error. For 50kHz to 100kHz, add 0.13% of range additional error.
6. Low-frequency performance: three filter settings are available: 3 Hz, 20 Hz, 200 Hz. Frequencies greater than these filter settings are specified with no additional errors.
7. Specifications are for 4-wire ohms function or 2-wire ohms using math null for offset. Without math null, add 0.2  $\Omega$  additional error in 2-wire ohms function.
8. The 10 A range is only available on a separate front-panel connector. Add 2 mA base per amp or inputs  $> 5$  A rms.
9. Specifications are for sinewave input  $> 5\%$  of range .  
For inputs within 1% to 5% of range, add 0.1% of range additional error.
10. Specifications are for the voltage measured at the input terminals. The 1 mA test current is typical. Variation in the current source will create some variation in the voltage drop across a diode junction.
11. Actual measurement range and probe errors will be limited by the selected probe. Probe accuracy adder includes all measurement and ITS-90 temperature conversion errors. PT100 Ro settable to  $100 \Omega \pm 5 \Omega$  to remove the initial probe error.
12. Specifications are for 60-minute warm-up and sine wave input unless stated otherwise. Specifications are for 1-second gate time .
13. Applies to sine and square inputs  $\geq 100$  mV. For 10 mV to  $< 100$  mV inputs, multiply % of reading error x10.
14. Amplitude 10% to 120% of range and less than 750 ACV.
15. Square wave input specified for 10 to 300 kHz.
16. The 3000V range is only available on a separate rear-panel connector.
17. The 50 A range is only available on a separate rear-panel connector.